



NADITBNC-MX

Female BNC 75 Ω input - male XLR cable end 110 Ω output.
Interface balanced and coaxial lines.

Features & Benefits

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match impedances 110 Ω to 75 Ω
- Match balanced to coaxial lines
- Simple to use, passive units

Technical Information

| Product | |
|------------------------|-------------|
| Title | NADITBNC-MX |
| Connection Type | Adapter |
| Gender | male |

| Electrical | |
|-----------------------|--|
| Frequencyrange | 0.1 - 6 MHz |
| Rated voltage | $\leq 5 \text{ V p-p}$ |
| VSWR | < 1.1 |
| Return loss | $> 26.4 \text{ dB}$ |
| Insertion Loss | $< 0.3 \text{ dB @ } 0.1 \text{ MHz to } 10 \text{ MHz}$ |

| Mechanical | |
|-----------------|--|
| Wiresize | |